



ID#PE297

## RANGER ROBOT

MODEL: RF40077104BHHR  
S.O.-890006641 3 01-09-001  
In-1700rpm/out-121rpm  
Hp-.5 Torque-800 lb. in  
Ration-14.08 Service-CL1  
Mtg-Pos VI  
Acme Transformer  
General Purpose Transformer  
Catalog No. T-3-53040-S Style SR  
Primary Volts 120X240 Wt. 20 Lbs  
Secondary Volts 1201240  
1.0 KVA 60 HZ 1 Phase

Winding Rise 115 'C  
% Impedance at 'C instructions 1-40  
Minimum Field Clearance 4 inches, vertical  
4 inches  
Enclosure Type 3R Outdoor  
Insulation System H-3180-1 Class 180  
Con-Evator Small Control Box  
Voltage-3X440/60  
Kw-1.37  
Fusemax 10-A  
Type-PGT Code-85T8  
Code-85T8



This list is subject to change without notice.

This specification sheet is confidential and is just a guide. Although obtained from sources deemed reliable, Premier Equipment makes no warranty or guarantee as to the accuracy of the information herein contained. It is the purchaser's responsibility to verify specifications.

PREMIER EQUIPMENT 29225 CHAGRIN BLVD, SUITE 250 BEACHWOOD, OH 44122

[www.buypremierequipment.com](http://www.buypremierequipment.com)

Ph: (216) 593-7000 Fax: (216) 593-0557 Toll-free (888) 897-1197